

Brother HL-2250DN :

- Install the driver.
 - Turn on the printer and connect the usb, network or parallel cable.
 - Go to the directory where the driver is.

Install LPR driver

```
$ sudo dpkg -i--force-allhl2250dnlpr-2.1.0-1.i386.deb  
cupswrapperHL2250DN-2.0.4-2.i386.deb
```

- Check if the LPR driver is installed.
\$sudo dpkg -l |grep Brother
- Configure a file
 - **\$sudo gedit /etc/printcap**
 - Edit the file according to your connection.
For USB Connection (Default)
Check if the parameter of ":lp" is ":lp=/dev/usb/lp0"
For Network Connection
replace ":lp" line to the following 2 lines
:rm=(ip address of your printer)\
:rp=lp\
For Parallel Connection
replace ":lp" line to the following line
:lp=/dev/lp0\

Save the file
 - Restart the print system.
Command(forlpr):/etc/init.d/lprrestart
Command(forlprng):/etc/init.d/lprngrestart
- Try a test print.