

Canon LBP 3500:

Open terminal and Install the packages

```
$ sudo dpkg -i cndrv cups-common_2.60-1_i386.deb  
cndrv cups-capt_2.60-1_i386.deb
```

Restart the printer

```
$ sudo /etc/init.d/cups restart
```

Add printer and start the Cannon Printer daemon.

```
$ sudo /usr/sbin/lpadmin -p LBP2900B -m  
CNCUPSLBP3500CAPTK.ppd  
-v ccp://localhost:59786 -E
```

```
$ sudo /usr/sbin/ccpdadmin -p LBP3500 -o /dev/usb/lp0
```

```
$ sudo /etc/init.d/cups restart
```

```
$ sudo /etc/init.d/cups status
```

Check the printer status

```
captstatusui -P LBP3500
```

If you are seeing the message “Ready to print”, you are done!. Else you may have to restart the system, repeat all the steps from step 4.

Start the printer service for every system startup

```
$ sudo gedit /etc/rc.local
```

Add **/etc/init.d/ccpd start** before the word “exit” , save the file and close